Huawei B315 juhend

1. Ruuteri kasutajaliidesesse logimine.

Ühenda ruuter LAN kaabli või WiFi võrgu abil (WiFi puhul kasuta WEP või WPA võtit mis on ruuteri põhja all). Ava brauser ning aadressiribale sisesta **192.168.8.1** algseaded sisselogimisel on USERNAME: **admin** / PASSWORD: **admin**

Peale mida kasutajaliides palub algse parooli ära muuta.

WAWEI	English	→ Help Log In attil 13 💭	¥ = 12 €3
Home Statistics SMS Update Settings	More		
Oxick Setup Configure Dial-op O Ethernet O WLAN Uter name.	Profile Settings	Step 1 of 3	
Security O Password System O APN			
	New Profil	a Not	
Log In User name: john Passeord: ****			
Privacy Policy 000-20	5 HUAWEI TECHNOLOGIES CO., LTD.	Copyright Notice	

 Ruuterisse sisse logimisel avaneb kohe kiirseadistus (Quick Setup). Tehase poolt on juba Elisa seaded sisestatud ja midagi muuta ei ole vaja v.a. kui kasutad staatilise IP teenust, sel juhul tuleb luua uus profiil (NEW PROFILE) kus APN: static

моске влаковала 🔷 т											^
← → Ŏ 192.168.8.1/html/quicksetup.html								1 ☆	= (a 0	· ···
					English \vee	Help admin Log Out					
						ati 🕂 💷					
	Home Statistics S	MS Update	e i <mark>Settings</mark> i Mo	re I							
	Quick Setup	0	onfigure Profi	le Settings		Shee 1 of 1					
	Dial-up	0	oningure Pron	ie oetangs		allep 1 01 0					
	Ethernet	0	Profile name:	elisa EE internet(default)	~						
	WLAN	0	User name:								
	Security	0	Password								
	System	0	APN:	internet							
					Name Orofile	Mart					
					New Product	No. of Concession, Name					
	Privacy Policy		🙌 (C) 2005-2015 HUAV	EI TECHNOLOGIES CO., LTD.		Copyright Notice					
									_		

Mobiilse interneti puhul jäta CONNECTION MODE: Auto reziimile

MODINE BIOJACCIARD ∧ T ← → ◯ 192.168.8.1/html/quidksetup.html					0 x	=	-	۵
	👐 HUAWEI		English	→ Help admin Log Out				9
	Home Statistics SMS	S Update Settings More						
	Quick Setup	Configure Etherne	et Settings	Step 2 of 3				
	Ethernet 0	Note: If your product does	not have an Ethernet port, you need a U	ISB-LAN adapter.				
	WLAN C	Connection mode:	Auto ERRAE a Damanic IR	1				
	Security C System C	The system chooses the best of	pppe Dynamic IP Static IP					
		Uter name: Password	LAN only					
				Back Next				
	Privacy Policy	🛻 (C) 2006-2015 HUAWEI TE	CHNOLOGIES CO., LTD.	Copyright Notice				

3. Järgnevas aknas on võimalik muuta WiFi võrgu nime ja parooli. (Kasutades seadistamisel WiFi ühendust, logib ruuter sind välja. Pead uue nimega Wifi võrguga ühendama)

Mocke projectional A					_	U	
← → Ŏ 192.168.8.1/html/quicksetup.html				□ ☆	= ∅	۵	
		English	✓ Help admin Log Out				
	SWE HUAWEI		ati 🗱 🗇				
	Home Statistics SMS	Update Settings More					
	Quick Setup	Configure WLAN Settings	Step 3 of 3				
	Dial-up O						
	Ethernet O	Name SSID (Service Set Identifier): Enter a character string, of up	to 32 characters in				
	WLAN O	length, as the name for your wireless local area network (WLAN).					
	Security O	SSID: HUAWEI-B315-F9A2					
	System O	WPA pre-shared key:					
			Back Finish				
	Privacy Policy	(C) 2006-2015 HUAWEI TECHNOLOGIES CO., LTD.	Copyright Notice				

4. Kui kohe alguses ruuteri sisselogimise parooli ei muutnud, saad seda teha SETTINGS-SYSTEM-MODIFY PASSWORD

toole broadband A									2
→ () 192.168.8.1/html/modifypassword.html						☆	= 6	8 6	Ô
			English	✓ Help admin Log Out					
	S HUAWEI			all 💷 🗆					
	Home Statistics SMS	6 Update <mark>Settings</mark> More	•						
	Quick Setup	Modify Passwor	d						
	Dial-up C								
	Ethernet O	Current password:							
	WLAN C	New password							
	Security C	Datament charaft	I can blockby blick						
	System C)	Low Model High						
	Device Information	Confirm password:							
	Diagnosis		Do not remind after login if password						
	Restore Defaults		strength is low						
	Rebot								
	Privacy Policy	🐥 (C) 2005-2015 HUAWE	TECHNOLOGIES CO., LTD.	Copyright Notice					

5. DLNA võimaluse aktiveerimine. MORE-DLNA menüüst valides **enabled** ning valid kas kausta või kõik failid (all)

voore prozenna ∧ ⊤ ← → O 192168.81/html/dra.html	👐 HUAWEI	English → Help admin Log Out attil 13 🕞	□☆ = Z & …
	Home Statistics SMS Upda Samba Server User Settings CCDA	Alter Settings More DLNA D.344 statu: E Enable O Daable Devotory: M E Systemed Alt, all lites is the connected USB storage device will be shared Asser Asser	
	Prinag Paley	C 2006-2015 HUM/ED TECHNOLOGIES CO., LTD. Copyright National	

6. Parema kiiruse saamiseks, soovitame teha lukustamist 4G'sse

						English V Help admin Log Out
M 🎺	AWEI					ati 🔃 💭
Home ⊨ Sta	atistics	SMS	Update	Settings	More	I
Quick Setup			Netw	vork Set	tinas	
Dial-up		0				
Mobile Connection	n		Netv	work		
Profile Manageme	ent		Prefer	rred mode:		4G only
Network Settings			Net	work Coarel		Recommend to select "Auto" if you don't know the network type.
Ethernet		0	Netv	work Search	1	Auto Ad
NLAN		0	Mode			
Security		0				
System		0				Apply
Privacy Policy				(C) 2006-201	15 HUAWELT	TECHNOLOGIES CO LTD Convrint Notice

7. PIN koodi maha võtmine (Elisa PIN kood - 1234).

- PIN operation "Disable"
- PIN code "1234"
- Vajutame "Apply"

Quick Setup		PIN Manageme	nt	
Dial-up	0			
Ethernet	0	PIN operation:	Disable V	
WLAN	0	PIN code:	••••	
Security	0	Remaining attempts:	3	
PIN Management				
Firewall Switch				
MAC Filter				Apply
LAN IP Filter				
Virtual Server				
Special Applications				
DMZ Settings				
SIP ALG Settings				
UPnP Settings				
NAT Settings				
Domain Name Filter				
DDNS				
System	0			
•				